



Set Up

1. Unpack your new Pyro Pro Par and inventory the following: One Pro Par. One owner's manual.
2. Mount the pro par on a light stand.
3. Connect the power cord to a grounded supply and it will power up.

Manual Operation

Your new LED Pro Par can be used with out a controller. To access the colors, chases or automatic fading functions press menu and refer to the highlighted part of the chart below.

Display	Setting	Function
ADDR	1 through 512	Press enter and use up or down to set DMX Channel.
ChMd	3Ch	Press enter to choose the 3 Channel DMX mode (See chart below).
	6Ch	Press enter to choose the 6 Channel DMX mode (See chart below).
SLMd	MASt	Press enter to choose to have this pro par control other pro pars.
	SLAu	Press enter to choose to have this pro par be controlled by a master pro par.
ShMd	SoUn	Press enter to choose to have the pro par change colors with the music.
	CoLo	Press enter and choose from 9 pre mixed color settings or automatic color change.
	FAde	Press enter and choose the speed of the color fading. SP1 for fast to SP8 for slow.
MAnu	red	Press enter and manually set the brightness of the red LEDs. (1-255)
	Gree	Press enter and manually set the brightness of the green LEDs. (1-255)
	bLue	Press enter and manually set the brightness of the blue LEDs. (1-255)
FhrS		Press enter to see the duration of the fixture.

DMX Operation

Three Channel Mode:		
Channel	Channel Value	Function
1	0---255	Red Brightness Control
2	0---255	Green Brightness Control
3	0---255	Blue Brightness Control

Six Channel mode:			
Channel	Channel Value	Function	
1	0---255	Red	Red Brightness Control
2	0---255	Green	Green Brightness Control
3	0---255	Blue	Blue Brightness Control
4	0----15	Auto	No Function
	15---255		Automatic color change from slow to fast
5	0---126	Strobe	No Function
	127--255		Strobe from slow to fast
6	0---255	Brightness	Over all fixture brightness
Important Notes:		Channels 1, 2, and 3 will not function unless channel 6 is turned above 33, The Auto function over rides the strobe function.	